


PPC-300 & PPC-300D Technical Manual



NTEP CC 08-041



Yamato
www.YamatoCorp.com

YAMATO CORPORATION
1775 S. Murray Blvd.
Colorado Springs, CO 80916 USA
Tel (719) 591-1500 Fax (719) 591-1045

YAMATO TECH CORPORATION
#112-19425 Langley By-Pass
Surrey, B.C. V3S 6K1 Canada
Tel (604) 533-2338 Fax (604) 533-0827

PPC-300 & PPC-300D Technical Manual

Table of Contents

I	Introduction	1
	Conventions	1
	Safety Precautions	1
II	Description	4
	Name and Function of Parts	4
	Specifications	5
III	Calibration	7
	Enter Test Mode	7
	Calibrate the Scale	8
IV	Setup	9
	Changing Parameters	9
	User Mode	10
	System Mode	10
	Factory Mode	10
	Parameter Tables	11
	Capacity Specific Table	17
V	Troubleshooting	18
VI	Wiring Diagram	20
VII	Parts List	21

PPC-300 & PPC-300D Technical Manual

I Introduction


This technical manual provides you with information on configuration and repair of the PPC-300 and PPC-300D. Setup and operating instructions can be found in the PPC-300 & 300D Operation Manual.


Before using the scale, carefully read, understand, and follow the “Safety Precautions” described in this manual. Observe the advice given in the “Directions for Use” section to ensure proper operation.

Conventions

The following conventions are used in this manual.

 **Danger** : Warns users about a procedure that could result in serious injury or death if not performed properly or if ignored.

 **Warning** : Warns users about a procedure that could result in injury or property damage if not performed properly or if ignored.

 **Caution** : Warns users about a procedure that could result in minor injury or damage to the scale if not performed properly or if ignored.


 : Indicates an action that must never be performed.

 : Indicates an action that must always be performed.


Note : Statements that provide additional information.

Safety Precautions

 **Danger - To Avoid Electric Shock**

 Do not step on, or place heavy or edged objects on the AC adapter cord.
Do not disconnect the AC adapter by pulling on the cord. Connect and disconnect the AC adapter by holding the plastic body of the AC adapter.
Do not connect or disconnect the AC adapter while the adapter body, cord, or your hands are wet.
Do not spray water onto or submerge the scale.

 **Danger - To Avoid Explosion and Fire**

 This scale is not an explosion-proof model. Do not use the scale in an atmosphere containing flammable gases or explosive fumes. A fire or an explosion can result.

PPC-300 & PPC-300D Technical Manual

I Introduction



Danger - To Avoid Fire and Electric Shock



Do not operate the scale if there is smoke or a burnt smell coming from the scale. Remove the batteries or unplug the AC adaptor immediately. After making sure there is no danger, consult your dealer. Never try to repair the scale yourself!



Warning



Do not step or sit on the scale. This will damage the scale and you could be injured. Do not insert your fingers into gaps or holes in the scale. You could be injured. If the LCD display should break, do not touch the liquid or broken glass from the LCD. The liquid is toxic if ingested, and the glass can be sharp. Be especially careful around children. Do not short, submerge or heat the batteries. They could burst and leak corrosive chemicals.



Place the item to be weighed in the center of the platform. Items placed on the edge of the platform may fall off and cause injury or damage. When weighing a heavy, large or unbalanced item, make sure the item is stable on the platform to prevent injury or damage. Place the scale on a stable, level surface to prevent injury or damage.



Caution



Do not lift or carry the scale by the platform. This can damage the scale. Carry and lift the scale with both hands using the hand grips on the side of the scale. Do not twist the platform. This can damage the scale. Do not shock load the scale. This can damage the scale. Do not push the indicator or keys with sharp objects. They can puncture or break the switch membrane panel. This scale is a sensitive weighing instrument, avoid physical shocks. If you drop something on the scale, overload the scale, step on the platform, or drop the scale, the scale may be damaged and lose accuracy. Never open the housing. The electronics may be damaged and you may be injured by sharp edges on the internal parts. Do not place the scale upside down. This could damage the load cell. Do not lick or place batteries in the mouth.



Use the specified adapter or batteries, and choose a suitable environment. If you do not, the weight readings may be inaccurate and the scale may be damaged. When the low battery indicator appears, replace all four of the batteries. When installing the batteries, install them according to the polarity markings in the case (+, -). If the scale will not be used for a long period, remove the batteries. Keep batteries out of the reach of small children. Dispose of batteries in accordance with all applicable regulations. If the scale becomes dirty, wipe it with a soft cloth. For stubborn stains, apply a little neutral detergent and then wipe the scale with a dry cloth. Do not use thinner, benzene, hot water, or chemical agents, all of which can cause deformation, discoloration, or deterioration of the scale.

PPC-300 & PPC-300D Technical Manual

I Introduction



To keep the scale working efficiently

Place the scale on a flat stable surface that will support the scale and the load.

Do not place the scale in an area exposed to direct sunlight or to wind currents from an air conditioner, otherwise, the measurements will not be accurate.

Do not place the scale near machines that create vibrations or electromagnetic disturbance, such as microwave ovens, portable phones, or large motors. This will affect the accuracy.

The operating temperature range is from -10°C to $+40^{\circ}\text{C}$ (14°F to 104°F). Do not subject the scale to sudden temperature changes. Allow the scale to adjust to new temperatures before use.

If the scale is sealed, do not break the seal. If you break the seal, the scale will not be considered legal for trade. In this case, contact your dealer.

Do not disassemble or modify the scale, you will void the warranty. Modified scales will not be legal for trade.




Remove the batteries when using the AC adapter. The scale will continue to draw power from the batteries, if they are installed, even with an AC adapter connected.

PPC-300 & PPC-300D Technical Manual

II Description

Name and Function of Parts




- | | |
|---|--|
| <ol style="list-style-type: none"> 1) ON/OFF Key 2) Zero Key 3) Mode Toggle 4) Tare Key 5) Net/Gross Key 6) Unit Toggle 7) User Parameter Mode 8) Test Mode 9) Battery Status 10) Bubble Level 11) Stable Indicator 12) Net Weight Indicator 13) Center of Zero Indicator 14) Bar Chart 15) Function Modes | <p>Press to turn the power on or to enter function mode. Hold to turn power off.</p> <p>Press to zero the display, select a digit, select the next parameter, or store a setting. Simultaneously press the Zero and Tare keys to enter user parameter mode.</p> <p>Press the ON/OFF and Zero keys simultaneously to toggle between function and normal weighing modes.</p> <p>Press to tare off the current load or to increment a digit. Simultaneously press the Zero and Tare keys to enter user parameter mode.</p> <p>Press to toggle between net and gross weight readings if a tare is entered, or to decrement a digit.</p> <p>Press the Net/Gross and Tare keys simultaneously to toggle through the available weight units.</p> <p>Indicates that the scale is in user parameter mode.</p> <p>Indicates that the scale is in test mode.</p> <p>Indicates approximate remaining battery capacity in thirds.</p> <p>Use to level the scale.</p> <p>Indicates the weight reading has stabilized.</p> <p>Indicates the displayed weight is a net weight.</p> <p>Indicates the scale is at zero gross load.</p> <p>Indicates relationship between load and desired weight. The exact meaning depends on the function mode in use.</p> <p>CHECK - The scale is in Checkweighing function mode.
 PACK - The scale is in Packing function mode.
 RANK - The scale is in Grading function mode.</p> |
|---|--|

PPC-300 & PPC-300D Technical Manual

II Description

Name and Function of Parts



Specifications

Weighing system: Strain-gauge load cell
 Platform: 9.0" x 7.9" (230 x 200 mm), stainless steel
 Capacities and divisions:

Kilogram	Pound	Ounce	Pound-Ounce*	Max. Tare
2 kg x 0.001 kg	4.4 lb x 0.002 lb	80 oz x 0.05 oz	5 lb x 0.05 oz	Capacity
4 kg x 0.002 kg	10 lb x 0.005 lb	160 oz x 0.1 oz	10 lb x 0.1 oz	Capacity
10 kg x 0.005 kg	22 lb x 0.01 lb	352 oz x 0.2 oz	22 lb x 0.2 oz	Capacity
20 kg x 0.01 kg	44 lb x 0.02 lb	704 oz x 0.5 oz	44 lb x 0.5 oz	Capacity
30 kg x 0.01 kg	60 lb x 0.02 lb	1056 oz x 0.5 oz	60 lb x 0.5 oz	Capacity

* Combined units, such as pound-ounce, are not legal-for-trade.


Weight display: PPC-300 - single display
 PPC-300D - dual display
 Type: 7 segment LCD
 Character size, etc.: 0.5" (13.5 mm) (W) x 1.2" (30 mm) (H), 5 digits
 Functions: One touch tare, battery charge indicator, auto-off timer, and check-weighing, packing and grading functions
 Housing: ABS resin
 Optional equipment: AC adaptor
 Power supply: 6 VDC - four "D" size batteries or optional AC adaptor
 Consumption: 0.12 W (max.)
 Battery life: ~ 1400 hours of continuous use with alkaline batteries
 Operating temperature: 14°F to 104°F (-10°C to 40°C)
 Operating humidity: 30% to 80% relative humidity (no condensation)
 Weight: PPC-300 - 2.5 kg
 PPC-300D - 2.6 kg

PPC-300 & PPC-300D Technical Manual

II Description

Specifications

Dimensions:




PPC-300 & PPC-300D Technical Manual

III Calibration


Enter Test Mode

Test mode provides access to calibration, system and factory parameter modes, and to some operational values. To enter test mode:

1. Remove the stainless steel pan and place the scale on its side.
2. Open the battery cover and remove the four screws in the deep wells. Remove the scale platform and close the battery cover.
3. Remove the two rear feet and the two screws that were covered by them. Replace the two feet if you will be calibrating the scale.
4. Remove the two screws towards the front of the scale.





5. Grasp both halves of the scale body and place the scale on its feet. Lift the upper housing up, rotating it towards the front to place it upside down in front of the lower housing without straining the load cell and power cables.
6. Short the two test mode jumpers. The scale should now read at or near five zeros, and the test mode indicator (⚠) should display.
7. Rotate the upper housing back onto the lower housing. Be careful not to pinch the load cell cable between the two housings.








Test mode displays the internal count, initial count, direct raw count, average raw count, battery check or A/D conversion value, and display segment check in sequence. Rotate through these displays using the  key.

PPC-300 & PPC-300D Technical Manual



III Calibration








Calibrate the Scale

Calibration can be done with pound or kilogram weights. Pound weights are the default setup, but this can be changed through factory parameter 50 (see section IV Setup, Factory Mode.) A three point calibration is also the default setup, but two and four point calibrations can be selected when beginning the calibration using the  key. Two point calibration is not recommended, since it is less accurate than three or four point calibration. Press the  key to exit calibration mode and return to test mode.

1. With the scale in test mode, displaying internal counts, and on its feet, place the platform back in place with the recess for the load cell screws aligned over the screws. The platform will wobble if it is placed on the scale 180 degrees out of alignment. Do not place weights on the scale platform if it is not steady.
2. Press  +  (see note) to enter calibration mode. Press the  key if you want to change the number of calibration points. Ensure there is nothing on the platform, then press the  key while the stable indicator is displayed.
3. For three point calibration, place one half of the scale's full capacity on the platform. Press the  key while the stable indicator is displayed.
4. Place the scale's full capacity on the platform. Press the  key while the stable indicator is displayed.
5. The scale should briefly display an 'F' followed by either 20000, 22000 or 30000 counts (depending on the scale capacity and on whether calibration was done with pound or kilogram weights.) The calibration was successful if the reading is within +/- 3 counts of the target number. Press the  key for a few seconds to turn the scale off and exit test mode.
6. If the scale displays error 103 the scale is either misconfigured, incorrect weights were use for the calibration, or the scale may be damaged. Check that the weights are one half of capacity, and full capacity. If the weights are correct, check the scale configuration using section IV Setup, Default Parameter Tables. If the setup is correct, follow the steps in section V Troubleshooting.

A four point calibration would use weights for one third of full capacity, two thirds of full capacity, and full capacity. A two point calibration would only use weights for full capacity. Two point calibration does not perform any linearity corrections, making it less accurate.

Note: Two key icons joined by a plus sign ( + ) means to press and hold the first key, press the second key, and then release both keys.



PPC-300 & PPC-300D Technical Manual

IV Setup

Changing Parameters

The scale setup is controlled by three groups of parameters that determine how the scale operates. These three groups are user parameters, system parameters and factory parameters.

User parameters (01 - 23) can be changed in both user mode and system mode. They are easily accessed, without breaking the seal or opening the scale housing, and control features such as function selection, function configuration, auto-off and units at startup. The user parameters are included in system mode for the convenience of the scale technician.

System parameters (30 - 39, C0 and C1) can be changed in system mode. They control functions that the scale technician may need to change under unusual circumstances, such as the stable reading configuration. Since these parameters can alter the accuracy of the scale, the seal has to be broken to access system mode through test mode.

Factory parameters (40 - 99, A0 - A5, and B0) can be changed in factory mode. They control functions that directly relate to the accuracy, capacity and divisions of the scale, and are rarely changed outside of the factory. Factory parameters are usually only changed if a different capacity load cell is installed, or if a non-standard configuration is desired. Since these parameters can alter the accuracy of the scale, the seal has to be broken to access factory mode through test mode.

Each parameter has two components, the parameter keyword and the parameter value. The first two digits are the keyword and determine which parameter is being viewed. The last three digits are the parameter value and determine how the selected parameter is configured.

While each mode is accessed differently, all modes use the same keys to select and change the parameter settings, as follows.

To select the desired parameter keyword, use the keys as follows:

- increase the keyword by one + - decrease the keyword by one

To change a parameter value, use the keys as follows:

- increase the value by one + - increase the value by ten
 - decrease the value by one + - decrease the value by ten

The arrows placed above the key and below the and keys illustrate each key's function when in any of the setup modes.





To save the last value changed it is necessary to advance to the next parameter before exiting the current parameter setup mode.


Note: Two key icons joined by a plus sign (+) means to press and hold the first key, press the second key, and then release both keys.


PPC-300 & PPC-300D Technical Manual


IV Setup

User Mode

With the scale on and in the normal display mode, press  +  to enter user mode.



Press the  key to cycle through the user parameters.


Press the  key for about three seconds to turn the scale off and exit user mode.







System Mode

Enter test mode (see Section III Calibration - Enter Test Mode.)

With the display showing initial counts, press  +  to enter system mode.





Press the  key to cycle through the user parameters.

Press  +  a second time to return to test mode, or press the  key for about three seconds to turn the scale off and exit system and test modes.







Factory Mode



Enter test mode (see Section III Calibration - Enter Test Mode.)

With the display showing initial counts, press  +  to enter calibration mode, then press  +  to enter factory mode.

Press the  key to cycle through the user parameters.

Press  +  to return to test mode, or press the  key for about three seconds to turn the scale off, and exit factory and test modes.



Note: Two key icons joined by a plus sign ( + ) means to press and hold the first key, press the second key, and then release both keys.

PPC-300 & PPC-300D Technical Manual

IV Setup

Parameter Tables

User Parameters			
Parameter	Function	Default	Settings
01	Function selection	000	000: Functions disabled 001: Packing enabled 002: Checkweighing enabled 003: Grading enabled
02	Number of grades	006	000: Grading suspended 001 - 015: 1 - 15 grades
03	Buzzer	000	000: Disabled 001 - 004: PPC-300WP only
04	Grade Stability	000	000: Real time grade display 001: Grade displayed at stable reading
05	Auto-off timer	003	000: Disabled 001: After idle for 5 minutes 002: After idle for 10 minutes 003: After idle for 15 minutes 004: After idle for 30 minutes 005: After idle for 60 minutes
06	Automatic tare	000	000: Disabled 001: Enabled (packing function only)
07	Flashing display	000	000: Disabled 001: Flash when under weight 002: Flash for acceptable weight 003: Flash when over weight 004: Flash when not acceptable weight 005: Flash when buzzer sounds
08 -19	Inactive	000	000: Do not adjust
22	Vibration compensation	000	000: Standard, highest response speed 001: Increased, slower response speed 002: Maximum, slowest response speed
23	Units at power on	001	000: kg 001: lb 002: oz 003: lb-oz

PPC-300 & PPC-300D Technical Manual

IV Setup

Parameter Tables

System Parameters			
Parameter	Function	Default	Settings
30	System ID	015	016: Change prohibited
31	Stable state sampling count	004	000 - 015
32	Stable state count	012	000 - 050
33	Very stable state count	008	000 - 050
34	Stable state collapse count	020	000 - 050
35	Stable state average count	006	000 - 015
36	Moving average count	003	000 - 001: Disabled 002 - 008: Average against sampling count
37	Multifunction data accumulation	000	000: Disabled 001: Enabled
38	Local multifunction setting	000	000: Enabled 001: Disabled
39	Display update rate	002	000: Disabled 001 - 015: Update counts
C0	Loading/unloading amount (DP)	004	004 - 255
C1	Beep at data transmission (DP)	000	000: Disabled 001: Enabled

PPC-300 & PPC-300D Technical Manual

IV Setup

Parameter Tables

Factory Parameters			
Parameter	Function	Default	Settings
40	Gravity compensatin	106	000: No compensation 001 - 029: For specified zone (Japan) 030 - 210: 9.76 to 9.85 m/s ² using $\frac{(g - 9.7600) \times 10^4}{5} + 30$
41	Scale mode	002	000: Fixed single increment 001: Multi-increment 002: U.S. mode 003 - 007: Do not use
42	Multi-increments Complex increment mode	000	000: Fixed accuracy, single increment 001: Fixed accuracy, 3 increments 002: Fixed accuracy, 2 increments 003: Increment change at 50% FS, 2 inc. 004: Increment change at 80% FS, 2 inc. 005: Increment change at 64% FS, 2 inc. 006: Increment change at 40% FS, 2 inc.
43	Weighing capacity mantissa, kg	*	000 - 099
44	Weighing capacity index, kg	*	001 - 004
45	Small capacity increment, kg	*	000: 1 001: 2 002: 5 003: 10 004: 20 005: 50 006: 100 007: 200
46	Location of decimal point, kg	*	000: 0 001: 0.0 002: 0.00 003: 0.000
47	Verification	000	000: Verified 001: Not verified
48	User mode calibration	000	000: Disabled 001: Enabled (47 must be set to 001)
50	kg or lb calibration	000	000: kg calibration 001: lb calibration
51	Weighing capacity mantissa, lb	*	000 - 099
52	Weighing capacity index, lb	*	000 - 004

* Value determined by capacity, see capacity specific table after parameter tables.

PPC-300 & PPC-300D Technical Manual

IV Setup

Parameter Tables

Factory Parameters			
Parameter	Function	Default	Settings
53	Location of decimal point, lb	*	000: 0 001: 0.0 002: 0.00 003: 0.000
54	Small capacity increment, lb	*	000: 1 001: 2 002: 5 003: 10 004: 20 005: 50 006: 100 007: 200
55	Weighing capacity mantissa, oz	*	000 - 099: Specify at lb (oz = lb x 16)
56	Weighing capacity index, oz	*	001 - 004
57	Location of decimal point, oz	*	000: 0 001: 0.0 002: 0.00 003: 0.000
58	Small capacity increment, oz	*	000: 1 001: 2 002: 5 003: 10 004: 20 005: 50 006: 100 007: 200
60	Type of decimal point	000	000: Period (.) 001: Comma (,)
61	Weighing unit	002	000: No unit 001: g 002: kg
62	Weighing unit display	001	000: Disabled 001: Enabled
65	Internal resolution	010	000: Do not use 001 - 255
66	Timer (ms)	035	000: Do no use 001 - 255
68	Over scale	005	000 - 010
70	Zero point range (FS%)	019	000 - 100
71	Positive zero point range %	012	000 - 100: Must be within range set in 70

* Value determined by capacity, see capacity specific table after parameter tables.

PPC-300 & PPC-300D Technical Manual

IV Setup

Parameter Tables

Factory Parameters			
Parameter	Function	Default	Settings
72	Zero key tare	000	000: Tare not cleared by zero key 001: Tare cleared by zero key
73	Zero tracking timing	006	000: Zero tracking disabled 001 - 050: Zero tracking at specified counts
74	Tare function	002	000: Tare disabled 001: One-time tare 002: Consecutive tare
75	Zero reset under tare	001	000: Zero reset under tare enabled 001: Zero reset under tare disabled
76	Normal or subtractive grading	000	000: Normal grading 001: Subtractive grading
77	Simple test mode	004	000: User mode enabled, test mode enabled 001: User mode disabled, test mode enabled 002: User mode enabled, simple test mode enabled 003: User mode disabled, test mode disabled 004: User mode enabled, test mode disabled
78	CPU motion clock	000	000: 6 MHz (PPC-300) 001: 8 MHz (DP-6500)
79	Grading accuracy improvement	000	000: Do not use 001: OEM setting
80	Combination matrix transmission	000	000: Disabled 001: Send displayed value 002: Send rank value
81	Packing weighing function	001	000: Locked out 001: Selectable
82	Checkweighing function	001	000: Locked out 001: Selectable
83	Grading function	001	000: Locked out 001: Selectable
85	Display hold function	000	000: Disabled 001: Enabled for greater than net + 20 d, #87 and switch key disabled
87	Adding weight under hold	000	000: Disabled 001 - 005: Update weight display when more than specified divisions added

* Value determined by capacity, see capacity specific table after parameter tables.

PPC-300 & PPC-300D Technical Manual

IV Setup

Parameter Tables

Factory Parameters			
Parameter	Function	Default	Settings
88	Span adjustment time delay	002	000: No delay 001 - 005: Delay of specified seconds
90	Mechanical zero 1	N/A	000 - 255: Automatically set during calibration, do not change
91	Mechanical zero 2	N/A	000 - 255: Automatically set during calibration, do not change
92	Mechanical zero 3	N/A	000 - 255: Automatically set during calibration, do not change
93	Span coefficient 1, small	N/A	000 - 255: Automatically set during calibration, do not change
94	Span coefficient 2, small	N/A	000 - 255: Automatically set during calibration, do not change
95	Span coefficient 3, small	N/A	000 - 255: Automatically set during calibration, do not change
96	Span coefficient 1, large	N/A	000 - 255: Automatically set during calibration, do not change
97	Span coefficient 2, large	N/A	000 - 255: Automatically set during calibration, do not change
98	Span coefficient 3, large	N/A	000 - 255: Automatically set during calibration, do not change
99	Region number and gravity for span adjustment	N/A	000 - 150: Automatically set during calibration, do not change
A0	Board sensitivity adjustment 1	N/A	000 - 099: Board sensitivity adjustment mantissa, x 1000
A1	Board sensitivity adjustment 2	N/A	000 - 255: Automatically set during board sensitivity adjustment, do not change
A2	Board sensitivity adjustment 3	N/A	000 - 255: Automatically set during board sensitivity adjustment, do not change
A5	Display of "lb:oz" unit	001	000: Enabled 001: Disabled
B0	Factory setting	*	000: Do not use 001 - 005: UDS-1V versions (Japan) 006 - 019: For specific OEM versions

* Value determined by capacity, see capacity specific table after parameter tables.

PPC-300 & PPC-300D Technical Manual

IV Setup












Capacity Specific Table

Capacity Dependent Parameter	Capacity				
	2 kg/4.4 lb/80 oz/5 lb-oz	4 kg/10 lb/160 oz/10 lb-oz	10 kg/22 lb/352 oz/22 lb-oz	20 kg/44 lb/704 oz/44 lb-oz	30 kg/60 lb/1056 oz/66 lb-oz
43	002	004	001	002	003
44	003	003	004	003	003
45	000	001	002	000	000
46	003	003	003	002	002
51	044	001	022	044	006
52	002	004	002	002	003
53	003	003	002	002	002
54	001	002	000	001	001
55	005	001	022	044	066
56	002	002	001	001	001
57	002	001	001	001	001
58	002	000	001	002	002
B0	015	016	017	018	019

PPC-300 & PPC-300D Technical Manual

V Troubleshooting








The scale automatically detects several errors. The following table describes the various errors that can be encountered, and provide user-level corrective actions. If these actions fail to correct the error, please contact a qualified scale technician.

Display	Condition	Action
	Low batteries.	Replace all four batteries with fresh batteries.
	Exhausted batteries, scale will shut off.	Replace all four batteries with fresh batteries.
	Scale will not turn on.	Verify that batteries are installed with the correct polarity. Replace all four batteries with fresh batteries. Verify proper adapter is connected to the scale and plugged into a powered outlet.
	Load over allowable limit at start up.	Remove all items from the scale platform and press the  key. Power the scale off and back on. Calibrate the scale.
	Load under allowable limit at start up.	Remove items wedged under the scale platform and press the  key. Power the scale off and back on. Calibrate the scale.
	Attempted to zero a load greater than allowed.	Remove all items from the scale platform and press the  key. Power the scale off and back on. Calibrate the scale.
	Zeroed the scale with a load on the platform, and then removed the load.	Remove all items from the scale platform and press the  key. Power the scale off and back on. Calibrate the scale.

Additional troubleshooting steps require the services of a qualified scale technician. Do not attempt to service the scale yourself.

PPC-300 & PPC-300D Technical Manual


V Troubleshooting

Display	Condition	Action
	Overload - there is too much weight on the scale platform.	Remove weight from the scale platform until the load is within the scale capacity.
	Negative gross weight reading greater than five divisions.	Replace the stainless steel pan on the scale platform, if removed. Remove all items from the scale platform and press the  key. Power the scale off and back on. Calibrate the scale.
	Sensor error.	Turn the scale off, wait one minute, and then turn the scale back on.
	Circuit error.	Turn the scale off, wait one minute, and then turn the scale back on.
	Controller error.	Turn the scale off, wait one minute, and then turn the scale back on.
	Displayed weight is inconsistent or unstable. Zero is unstable.	Remove all items from the scale platform and press the  key. Make sure the scale is on a stable and level surface. Adjust the feet to prevent wobble. Check for sources of wind, vibration or strong EMF (heating, airconditioning, motors, compressors, etc.)

Additional troubleshooting steps require the services of a qualified scale technician. Do not attempt to service the scale yourself.


PPC-300 & PPC-300D Technical Manual

VI Wiring Diagram



PPC-300 & PPC-300D Technical Manual

VII Parts List



PPC-300 & PPC-300D Technical Manual

VII Parts List

ITEM	PART NUMBER	DESCRIPTION	QTY/UNIT
1	YAM-1250-300001	Upper housing	1
2	YAM-1250-300002	Lower housing	1
3	YAM-1250-300003	Plastic platform	1
4	YAM-1250-300004	Battery box lid	1
5	YAM-1250-300005	Battery box thumbscrew	1
6	YAM-1250-300006	Sealing screw, A	1
7	YAM-1250-300007	Sealing screw, B	1
8	YAM-1250-300008	Front glass, vendor side	1
9	YAM-1250-300009	Front glass, customer side, PPC-300D only	1
10	YAM-1250-300010	Levelling legs	4
11	YAM-1250-300011	Battery padding	2
12	YAM-1250-300012	Adapter jack sealing film	1
13	YAM-1250-300013	Nylon clamp, A	1
14	YAM-1250-300014	Nylon clamp, B, PPC-300D only	2
15	YAM-1250-300515	Front mask, vendor side	1
16	YAM-1250-300016	Front mask, customer side, PPC-300D only	1
17	YAM-1250-300017	Serial number label	1
18	YAM-1250-300018	Capacity sticker (specify capacity)	1
19	YAM-1250-300019	Stainless steel platform cover	1
20	YAM-1250-300020	Platform rubber pads	4
21	YAM-1250-300021	Blank film, customer side, PPC-300 only	1
22	YAM-1250-300122	Load cell assembly, 2 kg / 4.4 lb	1
	YAM-1250-300222	Load cell assembly, 4 kg / 10 lb	1
	YAM-1250-300322	Load cell assembly, 10 kg / 22 lb	1
	YAM-1250-300422	Load cell assembly, 20 kg / 44 lb and 30 kg / 60 lb	1
23	YAM-1250-300023	Level indicator	1
24	YAM-1250-300024	Platform screws	4
25	YAM-1250-300025	Load cell assembly screws	4
26	YAM-1250-300026	Housing screws	3
27	YAM-1250-300027	CPU board screws	2
28	YAM-1250-300028	Load cell cable screw	1
31	YAM-1250-300031	Battery box screws	2
32	YAM-1250-300032	E-ring	1
33	YAM-1250-300033	Battery box retaining screw	1
34	YAM-1250-300034	Display board screws, customer side, PPC-300D only	2
35	YAM-1250-300035	Display board cable screws, PPC-300D only	2
36	YAM-1250-300036	CPU board	1
37	YAM-1250-300037	Display board, customer side, PPC-300D only	1
38	YAM-1250-300038	Battery box cable	1
39	YAM-1250-300039	Display board cable, PPC-300D only	1
40	YAM-1250-300040	Battery box	1
41	YAM-1250-300041	Ferrite core	1
not shown	YAM-1250-300042	Spacer, t = 1.0 mm	4
not shown	YAM-1250-300043	Hole plug, NSF	3
not shown	YAM-1250-300044	Leg collars, NSF	4
43	LHV-5000-300001	AC\DC adapter	1



YAMATO CORPORATION
1775 S. Murray Blvd.
Colorado Springs, CO 80916 USA
Tel (719) 591-1500 Fax (719) 591-1045

YAMATO TECH CORPORATION
#112-19425 Langley By-Pass
Surrey, B.C. V3S 6K1 Canada
Tel (604) 533-2338 Fax (604) 533-0827